

**REMARKS**


This Letter essentially restates the PCT Article 34 Amendments as it would apply to the English language specification.

The first PCT Article 34 Amendment was filed on April 18, 2005, by which claims 2, 4, 11, and 13 have been amended, claims 1, 3, 6, 8, 12, and 16 have been canceled, and the specification has been amended. On September 22, 2005, the second PCT Article 34 amendment was filed, by which claims 2, 5, 14 have been amended.

Attached is an English language translation of the Annexes to the international preliminary examination report under PCT Article 36 (APPENDIX A), in which all the changes made by the first and second PCT Article 34 Amendments are incorporated. Also, an English language translation of the specification and drawings of the international application (APPENDIX B), and a mark-up version of the amended specification in which all the changes made by the first and second PCT Article 34 Amendments are shown (APPENDIX C), are attached hereto.

Dated: May 17, 2006

Respectfully submitted,

By   
Toshikatsu Imaizumi  
Registration No.: L0046  
Limited Recognition Under 37 C.F.R. § 11.9(b)  
RADER, FISHMAN & GRAUER PLLC  
1233 20th Street, N.W.  
Suite 501  
Washington, DC 20036  
(202) 955-3750  
Attorney for Applicant

Application No. Not Yet Assigned

Docket No.: SEM-0010

Attorney Docket No. SEM-0010

## **APPENDIX A**

### **ENGLISH LANGUAGE TRANSLATION OF THE ANNEXES TO THE INTERNATIONAL PRELIMINARY EXAMINATION REPORT UNDER PCT ARTICLE 36**

Amended Specification and Claims under PCT Article 34

International Application No. PCT/JP2004/016626

Inventor: Kimiyoshi KOBAYASHI

Title: CHARGER AND DC-DC CONBERTER

Rader, Fishman & Grauer PLLC

Attorney Docket No. SEM-0010

## **APPENDIX C**

### **MARKED-UP VERSION OF ENGLISH LANGUAGE TRANSLATION**

Amended Specification and Claims under PCT Article 34

International Application No. PCT/JP2004/016626

Inventor: Kimiyoshi KOBAYASHI

Title: CHARGER AND DC-DC CONVERTER

Rader, Fishman & Grauer PLLC

DESCRIPTION

CHARGER AND DC-DC CONVERTER ~~HAVING THE SAME~~

TECHNICAL FIELD

[0001] The present invention relates to a charger that obtains electric power necessary for a fuel cell and to a DC-DC converter ~~having the charger~~.

BACKGROUND ART

[0002] Figs. 12 and 13 show a DC-DC converter having a charging function in which a cell, such as a conventional fuel cell or solar cell is used as an input source, and a load  $R_o$  and a secondary cell B are connected in parallel to an output end of the DC-DC converter. The DC-DC converter having a charger shown in Fig. 12 has means for controlling an input voltage, which is lowered due to output impedance when electric power is supplied, so as to become constant, thereby realizing constant input of electric power in which when an input supply power  $P_{in}$  is smaller than an output supply power  $P_{out}$ , the input voltage becomes constant, and an output voltage becomes a dropping state, and means for controlling the output voltage so as to become constant, in which when the input supply power  $P_{in}$  is larger than the output supply power  $P_{out}$ , the input voltage increases, (for example, see to Patent Document 1 for the solar cell).

[0003] Furthermore, Fig. 13 shows a charger shown includes a charging circuit 20 is connected to the secondary cell B, and the charger has a unit that controls an input voltage, which is lowered due to output impedance when electric power is supplied, so as to be constant, thus realizing constant input of electric power. In addition, in the charger circuit the input power  $P_{in}$  is set to be larger than the output power  $P_{out}$ , and a constant voltage control circuit and a constant current control circuit are provided in order to stably perform the charging of a current into the secondary cell B.

Patent Document 1: Japanese Unexamined Patent Application Publication No. 11-341699

## DISCLOSURE OF INVENTION

### Problems to be Solved by the Invention

[0004] In the case of the former, however, when the input supply power  $P_{in}$  is higher than the output supply power  $P_{out}$ , the input voltage rises. For this reason, specifically when a fuel cell is used as the input source, the fuel cell is deteriorated due to rapid change in voltage environments since it generates electric power by a chemical reaction.

[0005] On the other hand, in the case of the latter, in a charger using a cell such as a fuel cell or a solar cell having relatively large output impedance when electric power

is supplied as an input source  $V_{fc}$ , it is possible to realize constant input of electric power by controlling an input voltage, which becomes low due to output impedance when electric power is supplied, to be constant (when the input supply power  $P_{in}$  is smaller than the output supply power  $P_{out}$ ). In this case, if an output voltage is set to a dropping point (which is slightly lower than an output constant voltage) voltage, it is possible to make the charging current become constant without using the constant current control circuit. However, the conventional charger does not have the above-mentioned structure, so that there are problems, for example, generation of heat and a complicated circuit structure.

[0006] Furthermore, for example, a fuel cell generates electric power by way of a chemical reaction, so that since a change in a supply voltage will lead to degradation, it is thus preferred that a voltage during charging be constant. In addition, when charging reaches an end thereof, the input supply power  $P_{in}$  becomes higher than the output supply power  $P_{out}$ , and the output voltage becomes constant by performing constant voltage control, so that the input voltage increases. At this time, it is preferable to detect the increase in the input voltage and to stop the charging operation.

[0007] In view of the above problems, the present

invention provides a charger and a DC-DC converter having the charger capable of preventing an increase in the output voltage of a cell and thus of preventing deterioration of the cell by making electric power on the output side thereof equal to electric power on the input side of a fuel cell.

#### MEANS FOR SOLVING THE PROBLEMS

[0008] In order to solve the problems, a charger according to the present invention that charges a secondary cell through a converter for controlling input electric power from a cell having relatively large output impedance when electric power is supplied, such as a fuel cell or a solar cell as an input source, comprises a current control circuit having the secondary cell provided at an output end thereof, that is connected to the secondary cell, and supplies a charging current flowing into the secondary cell as a current value which is obtained from a control amount necessary for keeping an output voltage of the converter at a dropping voltage to be set.

[0009] Further, in the current control circuit, when charging to the second cell is started, the current control circuit performs constant current charging by using the charging current flowing into the secondary cell as a current value determined according to an input electric power value, and at an end period of the charging when the

voltage of the secondary cell reaches approximately an output voltage, the current control circuit stops performing constant control of the input electric power and detects a rise in an input voltage, thereby stopping the charging.

[0010] The current control circuit includes a comparing unit which compares the output voltage of the converter with a reference voltage and outputs the control amount and a constant current control unit that performs constant current control on the secondary cell on the basis of the control value.

Moreover, in the charger, the constant current control unit performs the constant current control using a semiconductor switch.

[0011] The constant current control unit includes a first level conversion unit which is connected to an output end of the comparing unit, the first level conversion unit being connected to a positive output end of the converter and a control terminal of the semiconductor switch, and a second level conversion unit which is connected to an output terminal of the semiconductor switch, the second level conversion unit being connected to a negative output end of the converter and a control terminal of a second semiconductor switch wherein an output terminal of the second semiconductor switch is connected to an input terminal of the secondary cell, and when charging to the



secondary cell is started, the current control circuit performs the constant current charging by using the charging current flowing into the secondary cell as a current value that is determined according to an input electric power value, and at an end period of charging when the voltage of the secondary cell reaches approximately an output voltage, the current control circuit stops performing the constant control of the input electric power and detects a rise in the input voltage, thereby stopping the charging.

[0012] The charger has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

[0013] A DC-DC converter according to the present invention, that uses, as an input source, a cell such as a fuel cell or a solar cell, having relatively large output impedance when electric power is supplied, comprises the above-mentioned charger, wherein a secondary cell and a load are connected in parallel to an output end of the DC-DC converter, in which when a current flowing through the load decreases, a current control circuit connected to the secondary cell increases a charging current flowing into the secondary cell, and when the current flowing through the load increases, the current control circuit decreases the

charging current flowing into the secondary cell, thereby keeping an output voltage at a dropping voltage to be set.

[0014] In the DC-DC converter, the current control circuit includes a comparing unit which compares the output voltage of the DC-DC converter with a reference voltage and outputs the control value, and a constant current control unit that performs constant current control on the secondary cell on the basis of the control value.

Furthermore, in the DC-DC converter, it is preferable that the constant current control unit performs the constant current control using a semiconductor switch.

[0015] In the DC-DC converter, the constant current control unit includes, a first level conversion unit which is connected to an output end of the comparing unit, the first level conversion unit being connected to a positive output end of the DC-DC converter and a control terminal of the semiconductor switch, and a second level conversion unit which is connected to an output terminal of the semiconductor switch, the second level conversion unit being connected to a negative output end of the DC-DC converter and a control terminal of a second semiconductor switch, wherein an output terminal of the second semiconductor switch is connected to an input terminal of the secondary cell, in which when a current flowing through the load decreases, the current control circuit increases a charging

current flowing into the secondary cell, and when the current flowing through the load increases, the current control circuit decreases the charging current flowing into the secondary cell, thereby keeping the output voltage at a dropping voltage to be set.

[0016] The DC-DC converter has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

#### ADVANTAGES

[0017] As described above, in the charger according to the invention, the current control circuit is connected to the secondary cell. When charging to the secondary cell is started, the current control circuit increases a charging current flowing into the secondary cell. When the voltage of the secondary cell reaches approximately an output voltage, the current control circuit decreases the charging current flowing into the secondary cell. Therefore, according to this structure, it is possible to make the output supply power constant as a whole and thus to control an input voltage (for example, the output of the fuel cell) to be constant. Furthermore, the DC-DC converter according to the present invention can have the same advantages as

those of the charger.

[0018] Further, the output voltage can be stabilized at a predetermined dropping point. Therefore, the invention is advantageous since stable electric power can be supplied to a load.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0019] Fig. 1 is a circuit diagram illustrating a charger according to a preferred embodiment of the present invention.

Fig. 2 is a circuit diagram illustrating an example of a main portion of the charger according to the embodiment of the present invention.

Fig. 3 is a circuit diagram illustrating another example different from that shown in Fig. 2.

Fig. 4 is a circuit diagram illustrating yet another example different from those shown in Figs. 2 and 3.

Fig. 5 is a circuit diagram illustrating still another example different from those shown in Figs. 2 to 4.

Fig. 6 shows time charts of the charger according to the present invention.

Fig. 7 is a circuit diagram illustrating another charger different from that shown in Fig. 1.

Fig. 8 is a circuit diagram illustrating a DC-DC converter according to another preferred embodiment of the present invention.

Fig. 9 is a graph of an operational waveform, showing an electric power characteristic when a current control circuit is not operated.

Fig. 10 is a graph of an operational waveform, showing an electric power characteristic when the current control circuit is operated.

Fig. 11 is a circuit diagram illustrating a DC-DC converter different from that shown in Fig. 8.

Fig. 12 is a circuit diagram illustrating a conventional DC-DC converter having a charging function.

Fig. 13 is a circuit diagram illustrating a DC-DC converter different from that shown in Fig. 12.

#### Reference Numerals

[0020] Vfc: INPUT SOURCE (FUEL CELL)  
Vset: VOLTAGE CONTROL INPUT  
Ro: LOAD  
B: SECONDARY CELL  
1: ~~DC-DC~~ CONVERTER  
2: OPERATIONAL STATE DETECTING CIRCUIT  
10, 10a, 10b, 10c, 10d: CURRENT CONTROL CIRCUIT  
11: COMPARING CIRCUIT  
12a, 12b, 12c, 12d: CONSTANT CURRENT CONTROL CIRCUIT  
20: CHARGING CIRCUIT

#A, #F: DIFFERENTIAL AMPLIFIER  
 #B, #D, #G, #H: COMPARATOR  
 #C: VOLTAGE DETECTOR  
 #E: AMPLIFIER  
 Q1: CONTROL SWITCH OF ~~DC-DC~~ CONVERTER 1  
 Q2, Q3a, Q3b, Q10: SEMICONDUCTOR SWITCH  
 R1, R2: RESISTOR  
 R3, R4, R5, R6, R7, R8, R22, R23: VOLTAGE-DIVIDING RESISTOR  
 Rm, R24: CURRENT DETECTION RESISTOR  
 Ref1, Ref2: REFERENCE VOLTAGE  
 D1: DIODE

#### BEST MODE FOR CARRYING OUT THE INVENTION

[0021] Fig. 1 is a circuit diagram illustrating a charger according to a preferred embodiment of the present invention. The charger shown in Fig. 1 uses a fuel cell having a relatively large output impedance  $Z$ , as an input source  $V_{fc}$ , when electric power is supplied. Although the fuel cell is used as the input source  $V_{fc}$ , any cell having relatively large output impedance, such as a solar cell, can be used as the input source  $V_{fc}$  in the present embodiment. The charger includes a ~~DC-DC~~ converter 1. A secondary cell B is connected to an output end of the ~~DC-DC~~ converter 1.

[0022] Also, voltage-dividing resistors R3 and R4 are

connected to the output end of the ~~DC-DC~~ converter 1. A current control circuit 10 is connected to a connection point between the voltage-dividing resistors R3 and R4. The current control circuit 10 is also connected to a negative terminal of the secondary cell B. When charging to the secondary cell B is started, the current control circuit 10 carries out the charging on the basis of a current value of the constant current, which is decided according to an input electric power value so that a charging current flowing into the secondary cell B is constant. When the voltage of the secondary cell B reaches approximately an output voltage so that the charging reaches the end thereof the current control circuit 10 stops the control for the constant input electric power, and stops the charging by detecting a rising input voltage. In this case, a detailed example of the current control circuit 10 will be described later.

[0023] The charger according to the present invention further includes a voltage comparator #C. The voltage comparator #C compares an output voltage signal detected by the voltage-dividing resistors R3 and R4 with a reference voltage Ref1, thereby performing level conversion thereon, and outputs a signal to a comparator #B connected to an output end of the voltage comparator #C.

[0024] The charger according to the present invention further includes a differential amplifier #A. The

differential amplifier #A receives a voltage control input Vset having an arbitrary value, for controlling a voltage input from the outside to the charger, and an output voltage of a fuel cell, that is, an input voltage Vfc of the charger, and outputs a control signal for controlling the input voltage Vfc to generate the same value as that of the voltage control input Vset.

[0025] In this case, the voltage control input Vset can be represented by the following expression:

$$V_{set} = V_{fc} * R_2 / (R_1 + R_2).$$

For example, if  $R_1 = R_2 = 1 \text{ k}\Omega$  and a cell output needs to be 5V,  $V_{set} = 5V * 1 \text{ k} / (1 \text{ k} + 1 \text{ k}) = 2.5 \text{ V}$ . Therefore, 2.5V can be input from the outside.

[0026] The comparator #B compares a voltage signal, which is obtained by converting the level of an output voltage Vbatt of the secondary cell by the voltage detector #C, with a control signal for stable control, which is output from a triangular wave oscillator (OSC), and outputs a driving signal to a control switch Q1 of the ~~DC-DC~~ converter 1 through an operational state detecting circuit 2, which will be described below.

[0027] The charger according to the present invention includes the operational state detecting circuit 2. The operational state detecting circuit 2 is a circuit that compares a compensation voltage with an output voltage of



the fuel cell every predetermined-time, and detects whether the fuel cell is available, in which when the output voltage of the fuel cell is lower than the compensation voltage, the operational state detecting circuit 2 stops the operation of the control switch Q1 of a switching power source, and when the output voltage of the fuel cell is higher than the compensation voltage, the operational state detecting circuit 2 normally operates the control switch Q1 of the switching power source. In this case, since the operational state detecting circuit 2 is provided for emergency measures, it may be omitted.

[0028] Another example of the current control circuit 10 will be described below with reference to Fig. 2. A current control circuit 10a according to the present embodiment includes a comparing circuit 11 that compares an output voltage  $V_{out}$  of the DC-DC converter with a reference voltage  $Ref2$  thereby outputting a control value, and a constant current control circuit 12a that performs constant current control on the secondary cell B by using the control value. The comparing circuit 11 includes a comparator #D that compares the output voltage with the reference voltage  $Ref2$ , converts the level of the voltage, and outputs a control value.

[0029] The constant current control circuit 12a includes voltage-dividing resistors R5 and R6. The voltage-dividing

resistor R5 has one end connected to a positive output end of the ~~DC-DC~~-converter 1. The voltage-dividing resistor R6 has one end connected to an output end of the comparator #D. Furthermore, a control terminal of a semiconductor switch Q2 is connected to a connecting point between the voltage-dividing resistors R5 and R6. The constant current control circuit 12a further includes voltage-dividing resistors R7 and R8. The voltage-dividing resistor R7 has one end connected to an output terminal of the semiconductor switch Q2. The voltage-dividing resistor R8 has one end connected to a negative output end of the ~~DC-DC~~-converter 1.

[0030] Furthermore, a control terminal of a second semiconductor switch Q3a is connected to a connection point between the voltage-dividing resistors R7 and R8. The second semiconductor switch Q3a is connected to a negative terminal of the secondary cell B. Accordingly, when an output voltage rises, the current control circuit 10a is controlled to turn on the semiconductor switch Q2 and the second semiconductor switch Q3a, so that electric power is supplied to the secondary cell B as a constant current and the output voltage of the ~~DC-DC~~-converter 1 falls to a voltage determined according to the reference voltage Ref2.

[0031] Meanwhile, when the output voltage falls, the current control circuit 10a is controlled to turn off the semiconductor switch Q2 and the second semiconductor switch

Q3a, so that the electric power supply to the secondary cell B is suppressed and the output voltage of the ~~DC-DC~~ converter 1 rises to a voltage determined according to the reference voltage Ref2.

[0032] Fig. 3 shows a detailed example of another current control circuit 10b. The current control circuit 10b includes a comparing circuit 11 that compares the output voltage of the charger according to the present embodiment with a reference voltage Ref2, and outputs a control value, and a constant current control circuit 12b that performs constant current control on the secondary cell B on the basis of the control value. The comparing circuit 11 includes a comparator #D that compares the output voltage of the charger with the reference voltage Ref2, converts the level of the voltage, and outputs a control value.

[0033] The constant current control circuit 12b includes voltage-dividing resistors R5 and R6. The voltage-dividing resistor R5 has one end connected to a positive output end of the ~~DC-DC~~ converter 1. The voltage-dividing resistor R6 has one end connected to an output terminal of the comparator #D. A control terminal of a semiconductor switch Q2 is connected to a connection point between the voltage-dividing resistors R5 and R6. The constant current control circuit 12b further includes voltage-dividing resistors R7 and R8. The voltage-dividing resistor R7 has one end

connected to an output terminal of the semiconductor switch Q2. The voltage-dividing resistor R8 has one end connected to a negative output end of the ~~DC-DC~~-converter 1.

[0034] A detection terminal of a comparator #G is connected to a connection point between the voltage-dividing resistors R7 and R8. An output terminal of the comparator #G is connected to a gate terminal of a second semiconductor switch Q3b which is, for example, a field effect transistor (FET). The second semiconductor switch Q3b is connected to a negative terminal of a secondary cell B. Furthermore, one end of a current detection resistor R24 is connected to a source terminal of the second semiconductor switch Q3b. Both ends of the current detection resistor R24 are connected to two input terminals of a comparator #H. An output terminal of the comparator #H is connected to a reference terminal of the comparator #G so as to carry out feedback. Therefore, the electric power is supplied to the secondary cell B as a constant current by turning on the semiconductor switch Q2 and the secondary semiconductor switch Q3b, so that the output voltage of the charger is controlled so as to fall to the voltage determined according to the reference voltage Ref2. At this time, since the highest value of the constant current can be limited by the voltage-dividing resistors R7 and R8, a charging current of the secondary cell B can be arbitrarily set, so that it

possible to realize a stable system.

[0035] Meanwhile, when the output voltage falls, the electric power to the secondary cell B is suppressed by turning off the semiconductor switch Q2 and the second semiconductor switch Q3b, so that the output voltage of the charger is controlled so as to rise to the voltage determined according to the reference voltage Ref2.

[0036] Furthermore, a detailed example of still another current control circuit 10c will be described with reference to Fig. 4. The current control circuit 10c includes a comparing circuit 11 that compares an output voltage Vout of the DC-DC converter with a reference voltage Ref2 and outputs a control value, and a constant current control circuit 12c that performs constant current control on the secondary cell B on the basis of the control value. The comparing circuit 11 includes a comparator #D that compares the output voltage of the charger with the reference voltage Ref2, converts the level of the voltage, and outputs the control value.

[0037] The constant current control circuit 12c includes voltage-dividing resistors R5 and R6. The voltage-dividing resistor R5 has one end connected to a positive output end of the DC-DC converter. The voltage-dividing resistor R6 has one end connected to an output terminal of the comparator #D. Furthermore, a control terminal of a

semiconductor switch Q2 is connected to a connection point between the voltage-dividing resistors R5 and R6. The constant current control circuit 12c further includes voltage-dividing resistors R7 and R8. The voltage-dividing resistor R7 has one end connected to an output terminal of the semiconductor switch Q2. The voltage-dividing resistor R8 has one end connected to a negative output end of the ~~DC-~~  
~~DC-converter 1~~.

[0038] Furthermore, a control terminal of a second semiconductor switch Q3 is connected to a connection point between the voltage-dividing resistors R7 and R8. The second semiconductor switch Q3a is connected to a negative terminal of the secondary cell B. Accordingly, the electric power is supplied to the secondary cell B as a constant current by turning on the semiconductor switch Q2 and the second semiconductor switch Q3a, so that the output voltage of the ~~DC-DC-converter 1~~ is controlled so as to fall to the voltage determined according to the reference voltage Ref2.

[0039] In addition, when the output voltage falls, the supply of electric power to the secondary cell B is suppressed by turning off the semiconductor switch Q2 and the second semiconductor switch Q3a so that the output voltage of the charger is controlled so as to raise the output voltage of the ~~DC-DC-converter 1~~ to a voltage determined according to the reference voltage Ref2.

[0040] The constant current control circuit 12c further includes a semiconductor switch Q10. The semiconductor switch Q10 has input and output terminals that are connected in parallel to the input and output terminals of the semiconductor switch Q2. The constant current control circuit 12c further includes voltage-dividing resistors R22 and R23. The voltage-dividing resistor R22 has one end connected to a positive output end of the ~~DC-DC~~-converter 1. The voltage-dividing resistor R23 has one end connected to an AC input terminal. A control terminal of the semiconductor switch Q10 is connected to a connection point the voltage-dividing resistors R22 and R23. Therefore, when a signal is input from an AC adaptor, a low-level AC is input to the AC input terminal from the outside, and at the same time a stop signal is sent to the converter. Furthermore, when the semiconductor switch Q10 is turned on to start charging with a current from the AC adaptor, the second semiconductor switch Q3a is turned on, and the secondary cell B is charged with a constant current. The charging current decreases as the charging voltage of the secondary cell B rises.

[0041] Fig. 5 shows a detailed example of yet another current control circuit 10d. The current control circuit 10d includes a comparing circuit 11 that compares the output voltage of the charger according to the present embodiment

with a reference voltage Ref2, and outputs a control value, and a constant current control circuit 12d that performs constant current control on a secondary cell B on the basis of the control value. The comparing circuit 11 includes a comparator #D. The comparator #D compares the output voltage of the charger with the reference voltage Ref2, converts the level of the voltage, and outputs the control value.

[0042] The constant current control circuit 12d includes voltage-dividing resistors R5 and R6. The voltage-dividing resistor R5 has one end connected to a positive output end of the ~~DC-DC~~ converter 1. The voltage-dividing resistor R6 has one end connected to an output terminal of the comparator #D. Furthermore, a control terminal of a semiconductor switch Q2 is connected to a connection point between the voltage-dividing resistors R5 and R6. The constant current control circuit 12d further includes voltage-dividing resistors R7 and R8. The voltage-dividing resistor R7 has one end connected to an output terminal of the semiconductor switch Q2. The voltage-dividing resistor R8 has one end connected to a negative output end of the ~~DC-DC~~ converter 1.

[0043] Furthermore, a detection terminal of a comparator #G is connected to a connection point between the voltage-dividing resistors R7 and R8. The comparator #G has an



output terminal connected to a gate terminal of a second semiconductor switch Q3b which is, for example, an FET. The second semiconductor switch Q3b is connected to a negative terminal of the secondary cell B. Furthermore, the second semiconductor switch Q3b has a source terminal connected to one end of a current detection resistor R24. The current detection resistor R24 has both ends connected to two input terminals of a comparator #H. An output terminal of the comparator #H is connected to a reference terminal of the comparator #G, so as to carry out feedback. Accordingly, when an output voltage rises, the electric power is supplied to the secondary cell B as a constant current by turning on the semiconductor switch Q2 and the second semiconductor switch Q3b, so that output voltage of the charger is controlled so as to fall to a voltage determined according to the reference voltage Ref2. At this time, since the highest value of the constant current can be limited by the voltage-dividing resistors R7 and R8, the charging current of the secondary cell B can be arbitrarily set, so that it possible to realize a stable system.

[0044] On the other hand, when the output voltage falls, the supply of the electric power to the secondary cell B is suppressed by turning off the semiconductor switch Q2 and the second semiconductor switch Q3b, so that output voltage of the charger is controlled so as to rise to a voltage

determined according to the reference voltage Ref2.

[0045] The constant current control circuit 12c further includes a semiconductor switch Q10. Input and output terminals of the semiconductor switch Q10 are connected in parallel to input and output terminals of the semiconductor switch Q2. The constant current control circuit 12c further includes voltage-dividing resistors R22 and R23. The voltage-dividing resistor R22 has one end connected to a positive output end of the DC-DC converter. The voltage-dividing resistor R23 has one end connected to an AC input terminal. Furthermore, a control terminal of the semiconductor switch Q10 is connected to a connection point between the voltage-dividing resistors R22 and R 23. Therefore, when a signal is input from an AC adaptor, a low-level AC is input to the AC input terminal from the outside, and at the same time a stop signal is sent to the converter. Further, when the semiconductor switch Q10 is turned on and charging begins with the current from the AC adaptor, the semiconductor switch Q3b is turned on and the secondary cell B is charged with a constant current. In this case, the charging current decreases as the charging voltage of the secondary cell B rises.

[0046] The charger having the above-mentioned structure is operated as set forth below: Figs. 6(a) to 6(e) show time charts of an input voltage  $V_{fc}$ , an input current  $I_{fc}$ , the

output voltage  $V_{out}$ , a cell voltage  $V_{batt}$ , and a charging current  $I_{ch}$ , respectively. If charging is started, the input voltage  $V_{fc}$  is lowered, as shown in Fig. 6(a). However, the output voltage  $V_{out}$  rises, as shown in Fig. 6(c). If the output voltage  $V_{out}$  exceeds the reference voltage  $Ref2$ , the comparator #D provided in the current control circuit 10 outputs a negative control value. The control value is output to the control terminal of the semiconductor switch Q2 through the voltage-dividing resistors R5 and R6 to cause the semiconductor switch Q2 to be turned on. Furthermore, the control value is also output to the control terminal of the second semiconductor switch Q3 through the voltage-dividing resistors R7 and R8 to cause the second semiconductor switch Q3 to be turned on. Then, the charging current  $I_{ch}$  flowing through the secondary cell B increases and the cell voltage  $V_{batt}$  also rises. When output supply power  $P_{out}$  becomes constant, constant electric power charging begins.

[0047] When the constant electric power charging begins, the input voltage  $V_{fc}$  becomes constant due to the constant electric power, as shown in Fig. 6(a). Meanwhile, the output voltage  $V_{out}$  becomes constant by a dropping voltage of the current control circuit 10, as shown in Fig. 6(c). Furthermore, when a current is supplied from the output terminal of the ~~DC-DC~~ converter 1 to the secondary cell B to

charge the secondary cell batt, the cell voltage  $V_{batt}$  gradually rises, as shown in Fig. 6(d). In addition, the charging current  $I_{ch}$  undergoes constant current control by the current control circuit 10 so that the constant current is maintained, as shown in Fig. 6(e).

[0048] For a predetermined period of time after charging begins, the constant electric power state continues. However, if the charging reaches the end thereof, the cell voltage  $V_{batt}$  reaches a value close to the output voltage  $V_{out}$ , whereby the constant current state is therefore not maintained. Accordingly, the charging current  $I_{ch}$  decreases, as shown in Fig. 6(e), and the output voltage  $V_{out}$  rises, as shown in Fig. 6(c), so that the constant control is carried out by the constant voltage control value of the ~~DC-DC~~ converter 1, which is set in the comparator #C. In this case, as the constant electric power state collapses, the input voltage  $V_{fc}$  begins rising, as shown in Fig. 6(a). Furthermore, since when the output voltage  $V_{out}$  rises, a small amount of the charging current  $I_{ch}$  flows, the cell voltage  $V_{batt}$  gradually rises, as shown in Fig. 6(d).

[0049] Further, when the operational state detecting circuit 2 detects that the input voltage  $V_{fc}$  begins rising, the control switch Q1 provided in the ~~DC-DC~~ converter 1 is turned off to stop the charging whereby the charger is available.

#### EXAMPLE 1

[0050] Next, a modified example of the charger according to the present invention is shown in Fig. 7. The charger shown in Fig. 7 receives a current control input  $I_{set}$  of an arbitrary value, for controlling a current input from the outside to a charger, and an output current of the input source  $V_{fc}$ , that is, an input current  $I_{fc}$  of the charger, and outputs a control signal for controlling the input current  $I_{fc}$  to have the same value as that of the current control input  $I_{set}$ . In the present embodiment, a current detection resistor  $R_m$  is provided at an output end of the input source  $V_{fc}$  to detect a voltage between input and output ends thereof. The input and output ends of the current detection resistor  $R_m$  are connected to input terminals of an amplifier #E, respectively. The amplifier #E amplifies the voltage to a current compensation voltage. Furthermore, as shown in Figs. 6(a) and 6(b), when the input current  $I_{fc}$  rises, the input voltage  $V_{fc}$  falls in proportion to the rise in the input current  $I_{fc}$ . For this reason, the input end of the current detection resistor  $R_m$  is connected to a negative input terminal of the amplifier #E, and the output end of the current detection resistor  $R_m$  is connected to a positive input terminal of the amplifier #E.

[0051] The charger according to the present embodiment

includes a differential amplifier #F, that receives the current control input  $I_{set}$  having an arbitrary value, for controlling a current input to the charger from the outside, and the output current of the input source  $V_{fc}$ , that is, the input current  $I_{fc}$  of the charger, and outputs a control signal to a comparator #B. The other structures are substantially the same as those of the charger shown in Fig. 1, so that a description thereof will be omitted for simplicity.

[0052] The charger according to the present embodiment is different from the charger shown in Fig. 1 in that it receives the current control input  $I_{set}$  having an arbitrary value, for controlling a current input from the outside to the charger, and the output current of the input source  $V_{fc}$ , that is, the input current  $I_{fc}$  of the charger and outputs the control signal. However, in this embodiment, when the input current  $I_{fc}$  increases, the input voltage  $V_{fc}$  falls in proportion to the increase in the input current  $I_{fc}$ . Therefore, the operation of the charger of the present embodiment is substantially the same as that of the charger shown in Fig. 1.

## EXAMPLE 2

[0053] Next, a circuit diagram of a DC-DC converter having a charging function according to an embodiment of the

present invention is shown in Fig. 8. The DC-DC converter shown in Fig. 8 uses, as an input source  $V_{fc}$ , a fuel cell having relatively large output impedance  $Z$  when electric power is supplied. Although in the present embodiment, the fuel cell is used as the input source  $V_{fc}$ , any cell having relatively large output impedance, such as a solar cell, can be used as the input source  $V_{fc}$ . An output end of a DC-DC converter 1 is connected in parallel a load  $R_o$  and a secondary cell B.

[0054] Voltage-dividing resistors  $R_3$  and  $R_4$  are also connected to the output end of the DC-DC converter 1. A current control circuit 10 is connected to a connection point between the voltage-dividing resistors  $R_3$  and  $R_4$ . The current control circuit 10 is connected to a negative terminal of the secondary cell B. When a current passing through the load  $R_o$  decreases, the current control circuit 10 increases a charging current passing through the secondary cell B. In addition, when the current passing through the load  $R_o$  increases, the current control circuit 10 decreases the charging current passing through the secondary cell B. In this way, the current control circuit 10 controls an output voltage to be maintained at a predetermined dropping voltage. Furthermore, in this embodiment, the detailed structure of the current control circuit 10 is the same as that of the above-mentioned

charger. Therefore, a description thereof will be omitted for simplicity.

[0055] The DC-DC converter according to the present invention further includes a voltage comparator #C. The voltage comparator #C compares an output voltage signal detected by the voltage-dividing resistors R3 and R4 with a reference voltage Ref1, converts the levels of the voltage signals, and outputs the voltage signal to a comparator #B connected to an output terminal thereof.

[0056] The DC-DC converter according to the present invention further includes a differential amplifier #A. The differential amplifier #A receives a voltage control input Vset having an arbitrary value, for controlling the input voltage of the DC-DC converter, and an output voltage Vfc of the fuel cell, and outputs a control signal for controlling the input voltage Vfc to have the same value as that of the voltage control input Vset.

[0057] Furthermore, the voltage control input Vset can be represented by the following expression:

$$V_{set} = V_{fc} * R_2 / (R_1 + R_2).$$

For example, if  $R_1 = R_2 = 1 \text{ k}\Omega$  and a cell output needs to be 5V,  $V_{set} = 5V * 1 \text{ k} / (1 \text{ k} + 1 \text{ k}) = 2.5 \text{ V}$ . Therefore, 2.5V may be input from the outside.

[0058] The comparator #B compares a voltage signal, which is obtained by converting the level of the output voltage of



the load R through the voltage detector #C, with a control signal for stable control, which is output from a triangular wave oscillator (OSC), and outputs a driving signal to a control switch Q1 of the DC-DC converter 1.

[0059] The DC-DC converter having the above-mentioned structure can be operated as set forth below. Furthermore, Fig. 9 shows an electric power characteristic when the current control circuit is not operated, and Fig. 10 shows an electric power characteristic when the current control circuit is operated. In the DC-DC converter according to the present invention, when a current flowing through the load  $R_o$  is higher than a rating (i.e., a dropping state), the current control circuit 10 is not operated, and a current is supplied from the output of the DC-DC converter and the secondary cell B, as shown in Fig. 9. The secondary cell B supplies a power through a diode D1.

[0060] Next, a case in which a load current  $I_{load}$  decreases will be described below. If the load current  $I_{load}$  decreases, as shown in Fig. 10, an output voltage  $V_o$  rises. If the output voltage  $V_o$  rises to exceed the reference voltage  $Ref2$ , a negative control value is output from the comparator #D provided in the current control circuit 10. The control value is output to the control terminal of the semiconductor switch Q2 via the voltage-dividing resistors R5 and R6, so that the semiconductor

switch Q2 is turned on. Furthermore, if the control value is output to the control terminal of the second semiconductor switch Q3 via the voltage-dividing resistors R7 and R8 so that the second semiconductor switch Q3 is turned on, a charging current  $I_{batt}$  flowing through the secondary cell B increases, and the output supply electric power  $P_{out}$  becomes constant. In this way, an output voltage  $V_o$  can be stabilized at a dropping point.

[0061] Then, a case in which the load current  $I_{load}$  increases will be described below. If the load current  $I_{load}$  increases, as shown in Fig. 10, the output voltage  $V_o$  falls. If the output voltage  $V_o$  falls below the reference voltage  $Ref2$ , a positive control value is output from the comparator #D provided in the current control circuit 10. The control value is output to the control terminal of the semiconductor switch Q2 via the voltage-dividing resistors R5 and R6, so that the semiconductor switch Q2 is turned off. Furthermore, if the control value is output to the control terminal of the second semiconductor switch Q3 via the voltage-dividing resistors R7 and R8 so that the second semiconductor switch Q3 is turned off, the charging current  $I_{batt}$  flowing through the secondary cell B decreases, and the output supply power  $P_{out}$  becomes constant. In this way, the output voltage  $V_o$  can be stabilized at a dropping point.

### EXAMPLE 3

[0062] Next, a modified example of the DC-DC converter having a charging function according to the present invention is shown in Fig. 11. The DC-DC converter shown in Fig. 11 receives a current control input  $I_{set}$  of an arbitrary value, for controlling a current input from the outside to a charger, and an output current of the input source  $V_{fc}$ , that is, the input current  $I_{fc}$  of the charger, and outputs a control signal, in the same manner as the charger shown in Fig. 7. The detailed structure of the DC-DC converter is substantially the same as that of the charger shown in Fig. 7 so that a description thereof will be omitted for simplicity. Furthermore, a fuel cell has a property in which, when the input current increases, the input voltage falls in proportion to the increases in the input current, as shown in Fig. 9. Therefore, the operation of the DC-DC converter according to this embodiment is substantially the same as that the DC-DC converter shown in Fig. 8.

### Industrial Applicability

[0063] According to the charger in accordance with the present invention, charging to the secondary cell begins with the current control circuit to which is the secondary cell is connected, in that if a charging current passing

through the secondary cell increases and the voltage of the secondary cell approaches to an output voltage, the charger is constructed to decrease the charging current passing into the secondary cell. Therefore, the present invention is advantageous in that an input voltage (for example, the output of a fuel cell) can be constantly controlled since the whole output supply power can become constant. Furthermore, the DC-DC converter according to the present invention can have the same advantages as those of the charger. Furthermore, since the output voltage can be stabilized at a predetermined dropping point. Therefore, the present invention is advantageous, since stable electric power can be supplied to a load.

## CLAIMS

1. (canceled)

2. (Amended) ~~The charger according to Claim 1, A~~  
charger that charges a secondary cell through a converter  
for constantly controlling input electric power from a cell  
having relatively large output impedance when electric power  
is supplied, such as a fuel cell or a solar cell as an input  
source, comprising: wherein, when charging to the secondary  
cell is started, the current control circuit performs  
constant current charging in which the charging current  
flowing into the secondary cell is used as a current value  
determined according to ~~an input electric power value~~ output  
voltage, and at an end period of the charging when the  
voltage of the secondary cell reaches approximately an  
output voltage, the current control circuit stops performing  
constant control of the input electric power ~~and detects a~~  
~~rise in an input voltage~~, thereby stopping the charging.

3. (Canceled)

4. (Amended) The charger according to Claim 2, ~~wherein~~  
~~the current control circuit includes a comparing unit which~~  
~~compares the output voltage of the converter with a~~

~~reference voltage and outputs a control amount, a semiconductor switch that is turned on and off according to the control amount, and a constant current control unit that performs constant current control by turning on and off the semiconductor switch wherein the current control circuit includes a comparing unit which compares the output voltage of the converter with a reference voltage and outputs a control amount, a semiconductor switch which is turned on and off based on the control value, and a constant current control unit that performs constant current control on the secondary cell based on the turning on and off.~~

5. (Amended) The charger according to Claim 4, wherein the constant current control unit includes a first level conversion unit which is connected to an output end of the comparing unit, the first level conversion unit being connected to a positive output end of the converter and a control terminal of the semiconductor switch, and a second level conversion unit which is connected to an ~~output~~ a negative terminal of the semiconductor switch, the second level conversion unit being connected to a negative output end of the converter and a control terminal of a second semiconductor switch, wherein an output terminal of the second semiconductor switch is connected to an input terminal of the secondary cell, and when charging to the

secondary cell is started, the current control circuit performs the constant current charging in which the charging current flowing into the secondary cell is used as a current value which is determined according to an ~~input electric power value~~ output voltage, and at an end period of charging when the voltage of the secondary cell reaches approximately an output voltage, the current control circuit stops performing the constant control of the input electrical power and detects a rise in the input voltage, thereby stopping the charging.

6. (Canceled)

7. (Original) The charger according to Claim 2, wherein the charger has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

8. (Canceled)

9. (Original) The charger according to Claim 4, wherein the charger has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage

control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

10. (Original) The charger according to Claim 5, wherein the charger has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

11. (Amended) A DC-DC converter that uses, as an input source, a cell such as a fuel cell or a solar cell, having relatively large output impedance when electric power is supplied, comprising:

~~the charger according to Claim 1,~~  
a secondary cell which is charged through a converter  
which performs constant input electric power control,

wherein a current control circuit is connected to a secondary cell in which the secondary cell and a load are connected in parallel to an output end of the a current control circuit, and

when a current flowing through the load decreases, the current control circuit increases a charging current flowing into the secondary cell, and



when the current flowing through the load increases, the current control circuit decreases the charging current flowing into the secondary cell, thereby keeping an output voltage at a dropping voltage to be set.

12. (Canceled)

13. (Amended) The DC-DC converter according to Claim ~~12~~ 11, ~~wherein the constant current control unit performs the constant current control using a semiconductor switch~~ the current control circuit includes a comparing unit which compares the output voltage of the DC-DC converter with a reference voltage and outputs the control amount, a semiconductor switch which is turned on and off based on the control amount, and a constant current control unit that performs constant current control on the secondary cell based on the turning on and off.

14. (Original) The DC-DC converter according to Claim 13, wherein the constant current control unit includes a first level conversion unit which is connected to an output end of the comparing unit, the first level conversion unit being connected to a positive output end of the DC-DC converter and a control terminal of the semiconductor switch, and

a second level conversion unit which is connected to an output terminal of the semiconductor switch, the second level conversion unit being connected to a negative output end of the DC-DC converter and a control terminal of a second semiconductor switch, wherein ~~an output terminal of~~ the second semiconductor switch is connected to ~~an input a~~ negative terminal of the secondary cell, when a current flowing through the load decreases, the current control circuit increases a charging current flowing into the secondary cell, and when the current flowing through the load increases, the current control circuit decreases the charging current flowing into the secondary cell, thereby keeping the output voltage at a dropping voltage to be set.

15. (Original) The DC-DC converter according to Claim 11, wherein the DC-DC converter has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

16. (Canceled)

17. (Original) The DC-DC converter according to Claim 13, wherein the DC-DC converter has functions of detecting a

voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

18. (Original) The DC-DC converter according to Claim 14, wherein the DC-DC converter has functions of detecting a voltage of the input source, of comparing the input voltage with a voltage control input that is arbitrarily set, and of controlling the input voltage to be constant on the basis of the control value.

## ABSTRACT

The invention provides a charger capable of keeping a charging current flowing through a cell constant, of reducing the number of components, and of realizing stable charging by controlling supply power on the output side thereof to be equal to supply power on the input side of a fuel cell. A charger has an output end connected to a secondary cell (B) and uses, as an input source ( $V_{fc}$ ), a cell having relatively large output impedance when electric power is supplied, such as a fuel cell or a solar cell. The charger includes a current control circuit (10) which is connected to the secondary cell and supplies a charging current flowing into the secondary cell as a current value which is obtained from a control value necessary for keeping an output voltage of a converter at a dropping voltage to be set.